

LTECH

Call Panel

Model: GOS



Manual

www.ltech-led.com

Product Introduction



- Preferably PC VO flame retardant material, safe and reliable.
- Widely used in various occasions, such as home emergency call, industrial control, building automation, public transportation and emergency evacuation.
- One-click feedback to reduce risks and losses.
- CNC aluminum alloy frame, a variety of color choices, perfect with different decoration styles.
- Standard 86 bottom box design, series combination.

Technical Specs

Model	GOS
Rated Voltage	250V~
Rated Current	1A
Working Temperature	-20°C~55°C
Standards	GB/T 17466.1
Net Weight	64g
Dimensions	86×86×36.5mm (L×W×H)
Package Size	102×102×70mm(L×W×H)
Colors	Lamborghini Gold/Bugatti Black/Ferrari Red/Pagani White
	Maserati Gray/Alfa Romeo Silver/24-Karat Gold/Noble Silver

Product Size

Unit:mm



Color Matching



Lamborghini Gold



Bugatti Black



Ferrari Red



Pagani White



Maserati Gray



Alfa Romeo Silver



24-Karat Gold



Noble Silver

Installation Steps

- ① Turn off the main power switch, and confirm that there is no cement and other attachments on the inner wall of the cartridge, reduce the length of the power cord in the cartridge to about 10CM, and use a flat-head screwdriver to pry open the Call Panel.



- ② Call Panel wiring mode: the COM end of the switch is usually the common end, the NO end is the normally open contact, and the NC end is the normally closed contact. If COM is connected to NO, the connection is off (normally on). Press the call button to connect. When COM is connected to NC, the connection is connected (normally closed). Press the call button to disconnect.



- ③ Fix the bottom box to the wall cassette with screws, so that the bottom box fits the wall.
- ④ Tilt the panel and fasten it on the bottom box, and open the main power switch.



After pressing the call switch, insert the call switch key into the reset hole and turn it clockwise by 45°. It can be reset;

After the reset is successful, turn the call switch key by 45° counterclockwise. Return to the original position and pull out.



Attentions

- Product installation and commissioning should be done by a qualified professional.
- LTECH products are and not lightningproof non-waterproof (special models excepted). Please avoid the sun and rain. When installed outdoors, please ensure they are mounted in a water proof enclosure or in an area equipped with lightning protection devices .
- Good heat dissipation will prolong the working life of products. Please ensure good ventilation.
- Please check if the working voltage used complies with the parameter requirements of products.
- The diameter of wire used must be able to load the light fixtures you connect and ensure the firm wiring.
- Before you power on products, please make sure all the wiring is correct.
- If a fault occurs, please do not attempt to fix products by yourself. If you have any question, please contact your suppliers.

 It's only suitable for safe use in areas with an altitude of 2000m and below.

Warranty Agreement

- Warranty periods from the date of manufacture: 2 years.
- Free repair or replacement services for quality problems are provided within warranty periods.

Warranty exclusions below:

Following conditions are not within the guarantee range of free repairing or replacement services:

- Beyond warranty periods.
 - Any artificial damage caused by high voltage, overload, or improper operations.
 - Products with severe physical damage.
 - Damage caused by natural disasters and force majeure.
 - Warranty labels and barcodes have been damaged.
 - No any contract or invoice signed by LTECH .
1. Repair or replacement provided is the only remedy for customers. LTECH is not liable for any incidental or consequential damage unless it is within the law .
 2. LTECH has the right to amend or adjust the terms of this warranty. The warranty that issues in writting shall prevail.

* This manual is subject to changes without further notice. Product functions depend on the goods. Please feel free to contact our official distributors if you have any question.